

Digital Thermometer

FEATURES

- IP65 water resistant
- Selectable temperature units, °C or °F
- Data hold function
- Maximum and minimum reading memory
- Automatic power off

SPECIFICATION

Temperature Range	-50°C~200°C/-58°F~392°F
Display Accuracy	±1°C (-20~120°C)otherwise ±2°C ±2°F (-4~248°F)otherwise ±4°F
Display resolution	0.1°C
Automatic power off	After idle for 10 minutes
Water resistant rating	IP65
Probe size	Φ3.5x122mm
Battery	LR44x1, 1.5V



OPERATION

Power ON/OFF

- Press 『ON-OFF』 to turn on.
- Press and hold for approximately 3 seconds to turn off.

Select Temperature Unit

- Press and hold 『°C/°F』 for 3 seconds and release to change the temperature unit.

Date Hold

- Press the 『HOLD』 button once to retain display reading and the °C or °F icon will be flashing.
- Press the button again will release the hold function and return to normal display.

Maximun/Minimum Reading Memory

- Press the 『MAX/MIN』 to display maximum reading.
- Press the button again to display minimum reading.
- Press the button once more to display normally.
- To reset the memory, switch the thermometer off then on.

*** Reset the memory once before taking new readings.**

NOTE

- Clean the probe immediately after each measurement to avoid cross contamination.
- When replacing battery, ensure all screws are tighten fully, otherwise it will affect the water resistant function.
- When the display becomes dim replace the battery.
- If there is any abnormal display or operation, switch off the thermometer once. All user setting will be reset to ex-factory settings.